



rakom.se

Radiokommunikation i Borås

Tvinnargatan 25 | info@rakom.se | Tfn: 033-723 22 10
507 30 Bråmhult | www.rakom.se | Fax: 033-13 88 71



PX-A6 Mini Compact Size 84x48x25mm



Scan Mode: Carrier/Time/Search
Busy Channel Lockout: Carrier/CTCSS/DCS
VOX Sensitivity: 0-9 level adjustable
Output Power: 0.5W(PMR)/ 2W(Professional)
TOT:0-270 selectable
50 CTCSS and 104 DCS
Channel Step: 5Khz/6.25Khz/12.5Khz/25Khz
DC 3.7V single Li-ion battery compatible
with mobile phone battery

Charging with USB cable 5V DC or 220V AC

www.puxingradio.com



PX-A6 MINI COMPACT RADIO

SPECIFICATION

- Frequency:400-470MHz
- Mini Compact Type
- All Channels Scan and
Priority Channel Scan
- 50 CTCSS and 104 DCS
- VOX Function
- Keypad Lock:Manual/Auto Optional
- Emergency Call
- Single Li-ion Battery;

GENERAL

Frequency Range	400~470MHz
Working Temperate	-20℃ ~ +50℃
Operating Voltage	DC 3.7V
Operate Mode	Simplex or Semi-duplex
Dimension	84mm x 48mm x 25mm(Not included antenna)
Weight	130g(Including battery)
Antenna Impedance	50Ω

TRANSMITTER

Frequency Stability	±2.5PPM
Output Power	UHF 2W
Max Frequency Deviation	≤5KHz
Audio Distortion	≤3%
Modulation Character	+3dB ~ -3dB
Adjacent Channel Power	≥65dB
Spurious Radiation	≤7.5μW
Occupied Bandwidth	≤16KHz

RECEIVER

RF Sensitivity	<0.2μV
Audio Distortion	≤3%
Audio Response	+2dB ~ -10dB
Co-Channel Rejection	≥-8dB
Adjacent Channel Selectivity	≥60dB
Intermodulation Rejection	≥65dB
Spurious Response	≥70dB
Blocking	≥80dB

Technical Specification Subject to Change Without Notice. The Photos Of The Products Featured In This Brochure May Not Be Of Actual Products

STANDARD ACCESSORIES



Xiamen Puxing Electronics Science&Technology Co.,Ltd.
ADD:No.11 Xianghong Road, Torch Gaoxin Zone,
Xiang'An District, Xiamen, Fujian, China
E-mail:sales@pxdz.com