

MC 1600

Dip switch

RGB



SUBSONIC RIGHT




SUBSONIC LEFT



GAIN RIGHT



IMPEDANCE RIGHT




CAPACITY RIGHT



GAIN LEFT



IMPEDANCE LEFT



CAPACITY LEFT



MC 1600

Dip switch

Impedance	1	2	3	4	5	6	7
20R	ON	ON	ON	ON	ON	ON	ON
40R	ON	---	ON	ON	ON	ON	ON
60R	ON	ON	---	ON	ON	ON	ON
80R	ON	---	---	ON	ON	ON	ON
100R	ON	ON	ON	---	ON	ON	ON
120R	ON	---	ON	---	ON	ON	ON
140R	ON	ON	---	---	ON	ON	ON
160R	ON	---	---	---	ON	ON	ON
180R	ON	ON	ON	ON	---	ON	ON
200R	ON	---	ON	ON	---	ON	ON
220R	ON	ON	---	ON	---	ON	ON
240R	ON	---	---	ON	---	ON	ON
260R	ON	ON	ON	---	---	ON	ON
280R	ON	---	ON	---	---	ON	ON
300R	ON	ON	---	---	---	ON	ON
320R	ON	---	---	---	---	ON	ON
340R	ON	ON	ON	ON	ON	---	ON
360R	ON	---	ON	ON	ON	---	ON
380R	ON	ON	---	ON	ON	---	ON
400R	ON	---	---	ON	ON	---	ON
420R	ON	ON	ON	---	ON	---	ON
440R	ON	---	ON	---	ON	---	ON
460R	ON	ON	---	---	ON	---	ON
480R	ON	---	---	---	ON	---	ON
500R	ON	ON	ON	ON	---	---	ON
520R	ON	---	ON	ON	---	---	ON
540R	ON	ON	---	ON	---	---	ON
560R	ON	---	---	ON	---	---	ON
580R	ON	ON	ON	---	---	---	ON
600R	ON	---	ON	---	---	---	ON
620R	ON	ON	---	---	---	---	ON
640R	ON	---	---	---	---	---	ON
660R	---	ON	ON	ON	ON	ON	ON
680R	---	---	ON	ON	ON	ON	ON
700R	---	ON	---	ON	ON	ON	ON
720R	---	---	---	ON	ON	ON	ON
740R	---	ON	ON	---	ON	ON	ON
760R	---	---	ON	---	ON	ON	ON
780R	---	ON	---	---	ON	ON	ON
800R	---	---	---	---	ON	ON	ON
820R	---	ON	ON	ON	---	ON	ON
840R	---	---	ON	ON	---	ON	ON
860R	---	ON	---	ON	---	ON	ON
880R	---	---	---	ON	---	ON	ON
900R	---	ON	ON	---	---	ON	ON
920R	---	---	ON	---	---	ON	ON
940R	---	ON	---	---	---	ON	ON
960R	---	---	---	---	---	ON	ON
980R	---	ON	ON	ON	ON	---	ON
1000R	---	---	ON	ON	ON	---	ON
1020R	---	ON	---	ON	ON	---	ON
1040R	---	---	---	ON	ON	---	ON
1060R	---	ON	ON	---	ON	---	ON
1080R	---	---	ON	---	ON	---	ON
1100R	---	ON	---	---	ON	---	ON
1120R	---	---	---	---	ON	---	ON
1140R	---	ON	ON	ON	---	---	ON
1160R	---	---	ON	ON	---	---	ON
1180R	---	ON	---	ON	---	---	ON
1200R	---	---	---	ON	---	---	ON
1220R	---	ON	ON	---	---	---	ON
1240R	---	---	ON	---	---	---	ON
1260R	---	ON	---	---	---	---	ON
1280R	---	---	---	---	---	---	ON
47k	ON	ON	ON	ON	ON	ON	---

Capacity	1	2	3	4	5
50p	---	---	---	---	---
100p	ON	---	---	---	---
150p	---	ON	---	---	---
200p	ON	ON	---	---	---
250p	---	ON	ON	---	---
300p	ON	ON	ON	---	---
350p	ON	---	ON	ON	---
400p	---	ON	ON	ON	---
450p	ON	ON	ON	ON	---
500p	ON	---	ON	ON	ON
550p	---	ON	ON	ON	ON
600p	ON	ON	ON	ON	ON

Gain	1	2	3	4	5
+32 dB	---	---	ON	---	---
+36 dB	---	ON	---	---	---
+40 dB	---	---	---	---	---
+44 dB	ON	---	ON	---	---
+48 dB	ON	ON	---	---	---
+52 dB	ON	---	---	---	---
+56 dB	ON	---	ON	ON	---
+60 dB	ON	ON	---	ON	---
+64 dB	ON	---	---	ON	---
+68 dB	ON	---	---	ON	ON

Subsonic	1	2	3
DC	ON	ON	---
6db / Oct	---	ON	---
12db / Oct	---	---	ON

Color	1	2	3
aus	---	---	---
blau	---	---	ON
grün	---	ON	---
türkis	---	ON	ON
rot	ON	---	---
lila	ON	---	ON
gelb	ON	ON	---
weiss	ON	ON	ON