

User Manual: "Top Pet Target" with Teach & Treat

Thank you for choosing the Top Pet electronic target "Top Pet Target"! We hope it will provide you and your dog with many positive training experiences.

Usage

- "Top Pet Target" is a complete product that detects when a dog steps on the target mat. The activation is indicated by sound, light, and can also be connected to a Teach & Treat reward machine for automatic treat dispensing.
- The product is intended for training purposes to increase the dog's understanding of hitting a specific surface, such as the contact area on an agility dog walk.
- "Top Pet Target" is suitable for dogs weighing between 1–60 kg.
- The cables on the target mat are non-detachable and must not be subjected to pulling or twisting forces.
- The equipment is not waterproof and must be protected from rain and moisture.
- The target mat must not be rolled up or folded, as this risks damaging the electronic sensor.

Setup

- Place the target mat on a firm and flat surface.
- Plug the cables into any available port on the electronic unit.
- Turn on the electronic unit by pressing the ON button.

Function

- The electronic unit features two different audio signals. If using the larger mat, this can be used to provide different sounds indicating which part of the mat has been activated.
- The electronic unit is equipped with a light signal consisting of 3 blue LED lights.

Connecting to the Teach & Treat Reward Machine

- The electronic unit can communicate wirelessly with the "Teach & Treat" reward machine. To use the units together, they must first be paired:
- Turn on the Teach & Treat machine.
- Press the small round button placed to the right of "Volume" until the green light starts flashing.
- Activate the Top Pet target mat by pressing it; the devices are now paired.
- Note: If you want to use the "Teach & Treat" with its own remote control again, you must pair the machine with the remote control in the same manner.

Buttons on the Electronic Unit

- ON: Turns on the electronic unit. The LEDs will flash as confirmation.
- S: Turns the sound off or on (sound is enabled by default).
- OFF: Turns off the electronic unit. A beep will sound as confirmation.

Battery

- The electronic unit is powered by 3 x AA 1.5V standard alkaline batteries (non-rechargeable).
- To extend battery life, the electronic unit shuts down automatically if no activity has been detected for the past 15 minutes. A beep will sound when the unit turns off.