



SENNHEISER

626 - 668 MHz

Frequenzbereich B / Frequency range B

**Zusatzinformationen für Systeme der Serie
evolution wireless IEM G4**

**Additional information for Sennheiser
evolution wireless IEM G4 systems**

DE

Für die Übertragung steht Ihnen folgender Frequenzbereich zur Verfügung:

Frequenzbereich	Bandbreite	Anzahl Frequenzen
626 - 668 MHz	42 MHz	max. 1680

Die Sender und Empfänger verfügen über jeweils 20 Kanalbänke, auf denen werksseitig Frequenz-Presets voreingestellt sind. Innerhalb einer Kanalbänke sind die Frequenz-Presets untereinander intermodulationsfrei. Sie sind nicht veränderbar.

In den Kanalbänken **U1 bis U6** können Sie in 25-kHz-Schritten Frequenzen frei einstellen und abspeichern. Diese sind unter Umständen nicht intermodulationsfrei.

Die Frequenz-Presets in den Kanalbänken **1 bis 20** sind in der Tabelle auf der folgenden Seite dargestellt.

Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen

In Ihrem Land gelten möglicherweise gesonderte Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen.

Informieren Sie sich vor der Inbetriebnahme des Produktes unter folgender Adresse:

www.sennheiser.com/frequency-information

EN

Transmitters and receivers are available in the following frequency range:

Frequency range	Bandwidth	Number of frequencies
626 - 668 MHz	42 MHz	max. 1680

Transmitters and receivers have 20 frequency banks respectively. Each of the channels in the frequency banks has been factory-preset to a frequency. These frequency presets within one frequency bank are intermodulation-free. They cannot be changed.

The frequency banks **U1 to U6** allow the user to store individual frequencies which are freely selectable in 25-kHz steps. It might be that these frequencies are not intermodulation free.

The table printed on the following page lists the frequency presets in the frequency banks **1 to 20**.

Conditions and restrictions for using frequencies

There may be special conditions and restrictions for using frequencies in your country.

Before putting the product into operation, find the information for your country at the following address:

www.sennheiser.com/frequency-information

Sennheiser electronic GmbH & Co. KG

Am Labor 1, 30900 Wedemark, Germany, www.sennheiser.com
Publ. 01/18, 578638/A01

Frequenzbereich B / Frequency range B: 626 - 668 MHz

Channel	Bank 1	Bank 2	Bank 3	Bank 4	Bank 5	Bank 6	Bank 7	Bank 8	Bank 9	Bank 10
1	626.200	630.200	638.200	646.200	654.200	662.200	630.200	638.200	646.200	662.600
2	626.600	630.600	638.600	646.600	654.600	662.600	630.600	638.600	646.600	664.200
3	627.200	631.200	639.200	647.200	655.200	664.200	631.200	639.200	647.200	665.400
4	628.400	632.000	640.000	648.000	656.000	665.400	632.000	640.000	648.000	666.400
5	629.800	633.200	641.200	649.200	657.200	666.400	633.200	641.200	649.200	667.200
6	631.400	635.600	643.600	651.600	659.600	667.200	634.800	642.800	650.800	667.800
7	632.200	637.800	645.800	653.800	661.800	667.800	638.600	646.600	654.600	626.200
8	634.200	636.900	644.900	652.900	660.900	626.200	639.900	647.900	655.900	626.600
9	637.600	638.500	646.500	654.500	663.400	626.700	642.600	650.600	658.600	627.550
10	638.900	641.200	649.200	657.200	666.900	628.800	643.100	651.100	659.100	628.250
11	641.600	646.000	654.000	663.100	667.400	630.100	644.800	652.800	660.800	628.700
12	646.100	647.100	655.100	663.600	626.200	634.200	645.500	653.500	661.500	629.550
13	648.400	649.900	657.900	665.900	626.900	636.500	648.900	656.900	626.200	633.550
14	652.500	656.100	663.900	667.600	629.600	639.000	650.800	658.800	628.100	635.050
15	655.000	658.000	665.600	627.100	631.700	640.500	658.100	666.100	630.600	637.750
16	659.600	663.200	667.700	629.000	634.900	644.900	660.600		641.900	640.050

Channel	Bank 11	Bank 12	Bank 13	Bank 14	Bank 15	Bank 16	Bank 17	Bank 18	Bank 19	Bank 20
1	626.200	630.200	626.200	630.200	626.200	630.200	638.200	646.200	654.200	662.200
2	626.600	631.400	626.600	630.600	626.600	632.400	640.400	648.400	656.400	662.600
3	627.200	633.000	627.200	631.200	627.200	634.800	642.800	650.800	658.800	663.150
4	628.000	635.000	628.400	632.000	628.000	636.000	644.000	652.000	660.000	663.850
5	638.200	637.200	629.200	633.200	628.500	636.800	644.800	652.800	660.800	664.850
6	639.400	646.600	654.200	634.800	629.200	637.400	645.400	653.400	661.400	665.650
7	641.000	649.200	655.600	637.000	662.200	637.800	645.800	653.800	661.800	666.750
8	643.000	652.200	658.000	662.200	663.100	631.100	639.100	647.100	655.100	667.650
9	645.200	662.200	659.600	664.600	664.600	640.300	648.300	656.300	664.300	626.200
10	655.600	662.600	654.700	667.800	666.300	643.000	651.000	659.000	667.000	627.550
11	658.600	663.200	657.250	662.700	667.400	645.100	653.100	663.200	626.200	629.900
12	661.200	664.000	660.050	666.100	663.750	646.200	654.200	663.700	626.700	631.450
13	662.900	626.300	663.200	663.550	633.900	649.000	657.000	667.000	630.700	634.600
14	663.600	627.000	664.300	666.650	637.300	657.100	664.100	667.700	639.600	637.950
15	666.300		667.750	626.550	643.400	658.600	666.000	626.700	644.900	642.200
16	667.400		667.050	627.450	649.900	662.400	667.500	628.200	646.400	643.650